

03009 TIME-DELAY SWITCH (Rail mounting)




USAGE AREAS

- Stairway space areas (Houses, offices, etc.)

CAUTIONS FOR USAGE & MOUNTING

- Mounting of the product must be done by an electrician.
- Turn off the network before mounting.
- Use 10A fuse to the supply input.
- Mount the device to smooth surface.


SPECIFICATIONS

Operating voltage	230-240V~ 50/60 Hz
Contact current 	10A
Time setting	Min. 2sec ± 1sec. - Max. 5min. ± 1min.
Protection Class	IP20 CLASS II
Max Watt	2000W  800W 

* Short-circuit protected

* Suitable for illuminated light switch

MOUNTING SCHEME



(L) Line, (LS) Lamp, (N) Neutral, (B) Button,
Do the mounting by following instructions below.

⊙ Automatic-continuous switch

When the switch turns to "Automatic" position, the device will operate by every push.

⊙ Automatic-continuous switch

When the switch turns to "Countinuous" position, the device will operate continuously. There is no need to puss button.

When the arrow turns to (+) direction, operation period/time will increase.

When the arrow turns to (-) direction, operation period/time will decrease.

TROUBLESHOOTING

MALFUNCTION	CAUSE	SOLUTION
After supply voltage the system, if the fuse turns off.	Bad wiring	Check the wiring
The device starts to operate itself	Bad wiring	Check the wiring
The device does not operate	Bad wiring	Check the wiring
The device turns off itself	Factory adjustment is at minimum time	Change the time period